Air-Dryable™ DNA LAMP Product Handling Guide		Storage and stability: Air-Dryable™ DNA LAMP is shipped on blue ice. On arrival store at -20 °C for optimum stability. Repeated freeze/thaw cycles should be avoided. Solutions should be mixed/equilibrated after each thawing to avoid phasing.	
		Expiry: When stored under the recommended conditions and handled correctly, full activity of the kit is	
Shipping:	Blue ice	retained until the expiry date on the outer box label.	
Catalog number:	MDX119	Safety precautions: Read and understand the SDS (Safety Data Sheets) before handling the reagents. Hardcopies of	
Batch No.:	See vial	the SDS will be provided with the first shipment, thereafter they will be available upon request.	
Concentration:	4x Store at –20 °C	Quality control: Meridian operates under ISO 13485 Quality Management System. Air-Dryable™ DNA LAMP and its components are extensively tested for activity, sensitivity, absence of nuclease contamination and absence of nucleic acid contamination.	
merid		<b>Notes:</b> For research or further manufactured use only.	

# Description

Air-Dryable<sup>™</sup> DNA LAMP is a glycerol-free mix for isothermal applications such as loop-mediated isothermal amplification (LAMP). It contains Bst DNA Polymerase (exo-), reaction buffer, dNTP and is provided with air-dryable excipients allowing ambient temperature stabilization of assays through air-drying. Air-Dryable<sup>™</sup> DNA LAMP has been designed for amplification of DNA targets. In order to produce an air-dried ambient-temperature stable LAMP reaction mix, specific primers and SYTO could be added to Air-Dryable<sup>™</sup> DNA LAMP for subsequent air-drying. Air-Dryable<sup>™</sup> DNA LAMP does not contain Mg<sup>++</sup>, which must be added prior to the amplification.

## **Kit components**

#### Table 1

## Component

Air-Dryable™ DNA LAMP, 4x

## **Users Guidelines**

Thawing during transportation does not affect product performance. Prior to use or storage at -20  $^\circ$ C, the thawed reagents must be thoroughly mixed by 10 inversions.

Please note that this mix <u>does not</u> contain magnesium. We suggest using 8 mM MgSO<sub>4</sub> as a starting concentration in the reaction. However, this might require optimization depending on the assay. It is advised to optimise Mg<sup>++</sup> concentration.

### Suggested LAMP reaction conditions:

The following protocol is for a standard 20  $\mu L$  LAMP reaction and is to be used as a starting point for optimization.

#### Table 1

Reagent	Volume	Final Concentration (1x)
Air-Dryable™ DNA LAMP	5 µL	1x
MgSO₄ (100 mM)	1.6 µL	8 mM
FIP/BIP Primers (20x)	1 µL	1.6 µM*
F3/B3 Primers (20x)	1 µL	0.2 μM*
Loop F/B Primers (20x)	1 µL	0.8 µM*
Sample DNA	variable	> 10 copies
Water (ddH <sub>2</sub> O)	to 20 μL	

\*Primer ratio needs to be optimised.

Incubate at 65 °C for 60 minutes.

Meridian Life Science Inc. USA

Tel: +1 901 382 8716 Fax: +1 901 382 0027

## Air-Drying

For air-drying protocols, please consult our "Air-Drying User Guideline".

### **General Guidelines**

Air-Dryable<sup>™</sup> DNA LAMP is compatible with fluorescence detection methods such as intercalating dyes (e.g. SYTO-82).

If analysing the LAMP products requires opening the reaction tubes, it is strongly recommended to carry out the analysis in a separate/designated area to avoid contamination.

It is recommended to include a no-template control (NTC) to verify product specificity.

## **Associated Products**

Product	Cat. No.
High Conc. Glycerol-Free Bst	MDX018
Inhibitor-Tolerant Bst Buffer, 10x	MDX019
Lyo-Ready™ LAMP Mix	MDX097
Air-Dryable™ RNA/DNA LAMP	MDX118

### **Technical Support**

For any technical enquiries, please contact our Technical Support team via email at: mbi.tech@meridianlifescience.com